



45 or 60 amps at
12, 24 or 48 volts

Shown with optional meter

TriStar™

THREE FUNCTION SOLAR CONTROLLER

- Fanless design for long-term reliability
- Fully Adjustable with DIP switches for seven digital presets
- Rated for operation at temperatures up to 60°C ambient
- Additional custom settings via RS-232

"It is a Morningstar, what do you expect! It is great!"

Three-function Pulse-Width Modulation (PWM) controller for larger systems, providing reliable PWM solar battery charging or load control or diversion regulation. PWM technology controllers are ideal for use in solar energy situations where 36 or 72 cell PV modules are available and the site is unshaded with no physical space limitations. TriStar models incorporate advanced thermal design requiring no cooling fans, which ensures long-term reliability with no moving parts to fail-- a unique feature among higher-powered controllers.

- » **Built for reliability and performance**, with an oversized heatsink and over-spec'd components
- » More information with LED indicators. Optional meter displays extensive system and controller information in five languages; **automatic self-test and reset communications capability** with RS-232 port, connects to a PC for custom settings, data logging, remote monitoring and control
- » **"Speaks" Modbus, and also SNMP** (with the optional EMC-1 adaptor) for monitoring and control in network applications
- » **Extensive electronic protection** against reverse polarity, short circuits, overcurrent, and excessive temperature
- » **Detailed battery programming** options allow for advanced battery support for the latest Lithium, Nickel Cadmium, and Lead Acid battery types.

KEY FEATURES AND BENEFITS

• High Reliability

Large heat sink ① and conservative design enables operation at up to 60°C ambient.

• More Power

Ratings to 60A at 48VDC will handle solar arrays of up to 3.2kW of continuous power.

• Communications Capability

RS-232 ② connects to a personal computer for custom settings, data logging and remote monitoring and control.

• Fully Adjustable

DIP switch ③ provides user with a choice of 7 different digital presets and custom settings via RS-232.

• Extensive Electronic Protections

Fully protected against reverse polarity, short circuit, overcurrent, high temperature and overvoltage.

• Simple Mechanical Interface

Larger power terminals ④ and conduit knockouts ⑤. Extra space for wire turns. Fits on power panels.



• Better Battery Charging

Connecting battery sense wires ⑥ and optional remote temperature sensor ⑦ will improve control accuracy. Constant voltage series PWM algorithm increases battery capacity and life.

• More Information

3 LED's ⑧ to indicate status, faults and alarms. Optional meter ⑨ displays extensive system and controller information, automatic self-test and reset capabilities. Meter connection via RJ-11 phone jack ⑩.

• Easy to Reset

Pushbutton ⑪ provides manual reset and stop/start battery equalization or load disconnect.

• Low Telecom Noise

DIP switch setting will change PWM to "On-Off" battery charging.

Technical Specifications

Versions	TS-45, TS-60 and TS-60M		
Electrical			
Rated solar, load or diversion current	TS-45 45A TS-60 60A TS-60M 60A		
System Voltage	12, 24, 48V		
Accuracy	12/24V 48V	≤0.1% ±50mV ≤0.1% ±100mV	
Minimum voltage to operate	9V		
Maximum solar voltage (Voc)	125V		
Self-consumption			
Controller	<20mA		
Meter	7.5mA		
Mechanical			
Dimensions	Height: 26.0cm/10.3 in Width: 12.7cm/5.0 in Depth: 7.1cm/2.8 in		
Weight	1.6kg/3.5lb		
Largest Wire	35mm²/2 AWG		
Conduit knockouts	Eccentric 2.5/3.2 cm (1.0/1.25 in)		
Enclosure	Type 1, indoor rated IP 20		
Environmental			
Ambient operating temperature range	Controller -40°C to +60°C Meter -40°C to +60°C		
May derate above the following temperature*	TS-PWM-60 and TS-PWM-45 = 55°C		
Storage temperature	-55°C to +85°C		
Humidity	100% (non-condensing)		
Tropicalization	Conformal coating on both sides of all printed circuit boards		

Electronic Protections

- Reverse polarity protection (any combination)
- Short-circuit protection
- Overcurrent protection
- Lightning and transient surge protection using 4500W transient voltage suppressors
- High temperature protection via automatic current reduction or complete shutdown
- Prevents reverse current from battery at night

Certifications

- CE Compliant
- ETL Listed (UL 1741)
- cETL (CSA-C22.2 No.107.1-95)
- TUV (IEC 62109-1)
- Complies with U.S. National Electric Code
- Manufactured in a certified ISO 9001 facility
- MET Labs (EN 60335-1, EN 60335-2-29)

Charge Control

1



1

- » Constant voltage series PWM design to provide highly efficient battery charging
- » 4-stage charging to increase battery capacity and life: bulk charge, PWM regulation, float and equalize
- » Parallel for larger solar arrays up to 300 amps or more

2

- » Starts large loads including motors and pumps with no damage to controller
- » Allows inrush current to 300 amps
- » Electronic short-circuit and overload protection with automatic reconnect
- » LVD is current compensated and has a delay to avoid false disconnects

3

- » May be used for solar, wind or hydroelectric
- » To protect against battery overcharge, excess energy is diverted from the battery to an alternate DC resistive load
- » PWM reduces power into diversion load during overcurrent conditions

Options

- **TriStar Meter-2 (TS-M-2)** — Included with the TriStar-60M, this 2 x 16 character LCD display mounts to controller and provides system and controller information, data logging (90 days internally logged), bar graphs, and choice of five languages. The TriStar 60 amp version is available with optional factory installed meter, TS-MPPT-60M

13.5v	25c	12.3A
1234.5Ah	FLOAT	



14.4 V	1135	7Ah
12.3 V	11.3	kWh

- **TriStar Remote Meter (TS-RM-2)** — Includes 30 meters of cable for mounting meter away from the controller
- **Remote Temperature Sensor (RTS)** — Provides temperature compensated charging by measuring temperature at the battery (10 meter cable)
- **Ethernet Meterbus Converter (EMC-1)** — IP based network and internet connectivity
- **MeterHub (HUB-1)** — Allows multiple Morningstar products to communicate over a Meterbus network
- **Relay Driver (RD-1)** — Logic module providing high level system control



* Based on Bulk charging operation, unvented enclosure. The controller may derate with lower temperatures during PWM charging operation.